



RF EP-2810-4ZRC CONTROLLER



RF LED RGB Controller SR-2810-4ZRC 4 Zones

- Remote LED Dimmer
- Programmable rgb controller (note the "P" in the center of the color wheel)
- High sensitive & high stable touch color wheel, fast & precise color control.
- Enable to control 4 zones separately. Each zone can switch on/off separately.
- Changing modes of 4 zones can be synchronized without any confusion.
- Adjustable changing speed with 8 levels.
- Enable to set changing modes freely by clicking or slide touching on color wheel.
- To work with power repeater to expand output unlimitedly.

SPECIFICATIONS

SENDER: (MODEL: EP-2810-4Z-RC)

Operation voltage: 4.5VDC
 Operation frequency: 434MHZ / 868MHZ
 Battery: 3pcs 7 AAA battery.

RECEIVER: (MODEL: EP-1006-8-EA-4Z-CVC)

Input voltage: 12-36VDC
 Output voltage: 12-36VDC
 EP-1006-8-EA-4Z-CVC: 3 channels x 8A, 3 channels x (96-288W) - Constant Voltage

RECEIVER: (MODEL: EP-1006-350-EA-4Z-CCC)

Input voltage: 12-36VDC
 Output voltage: 12-36VDC
 EP-1006-350-EA-4Z-CCC: 3 channels x 350mA, 3 channels x (4.2-12.6W) - Constant Current

RECEIVER: (MODEL: EP-1006-1000-EA-4Z-CCC)

Input voltage: 12-36VDC
 Output voltage: 12-36VDC
 EP-1006-1000-EA-4Z-CCC: 3 channels x 1000mA, 3 channels x (8.4-25.2W) - Constant Current



EPIC™ GLOBAL SYSTEM

BEYOND THE LIMITS!